

**Install in accordance with national and local electrical codes.  
All installation works must be performed with specialized personnel.**

**PUSH DIM , ON/OFF SWITCH**

Ignore	To avoid reaction on AC spike	< 0.05 sec.
Short push	Push to turn ON-OFF	0.1~1sec.
Long push	Dimming up or down	0.1~10sec.
Reset push	Setting light to 100%	> 11 sec.

Maximum number of drivers up to 10pcs.  
Maximum length of the cable, from push button to last driver is 20 meter.  
Factory setting at 100%.  
When the light is lower than 10% it will always dim up,  
or when the light output is higher than 90% it will always dim down.

